



WWW.HOBBYHOBBY.IT

User Manual CS-B800

Thank you very much for buying our wireless A/V transmission products. Please read the instruction below carefully before using it.

- Please install it at the place where the children can not touch;
- Do not expose it at the damp place for preventing it from water or protecting people from electric shock;
- Please use the transformer produced by our company, if not, our company will not be in charge of any damage incurred by the product;
- Our company will not be responsible for any damage incurred by your amending or dismounting without permission;
- Do not touch the emission antenna in case you will be burned when the transmitter is electrified.

Specifications of the Transmitter:

Model	Voltage	Current	Output Power	Frequency	Video Output	Audio Carrier Wave
CS-B800	DC 12 V	260mA	800mW	1.08GHz~1.36GHz	1Vp-p (FM)	5.5MHz

Corresponding Channels with frequencies:

Channel	4	5	6	7	8	9	H	C
Frequency	1.08G	1.12G	1.16G	1.2G	1.24G	1.28G	1.32G	1.36G

Installing:

- The cable for TX of 5 plugs for connecting the transmitter, camera, and power supply. One point of the cable is connected with the transmitter, and on the other point, there're 4 plugs with red, yellow, white and black. The red plug is connected to the power supply (DC12V, 1A or battery); the white and yellow plugs are connected with the camera's audio and video; and the black plug is connected with the camera's power input jack.
- Push the CONTROL button, then you may choose the channels. Meanwhile, push it and last it for several seconds, you can close the digital display and turn into saving time mode. Then push it again, then reply. This function is to lock channel, so as to avoid mistakenly operation.
- Set the transmitter and receiver in the same channel, then you can receive the A/V signals.
- If more than one transmitter is to be installed and use only one receiver, e.g., operating 2 transmitters with one receiver, set transmitter A to CH1 and set transmitter B to CH2;

Set receiver channels:

Push the CONTROL button to CH1 and MIDDEL lighting, then push the CONTROL button for two sec. to AUTO lighting;

Push the CONTROL button to CH2 and MIDDEL lighting, then push the CONTROL button for two sec. to AUTO lighting;

Push the CONTROL button to AUTO lighting, and now the receiver can auto-change between the two transmitters for A/V signals.

AGGIORNAMENTO 15/12/2011

Alimentazione trasmettitore: 12V oppure lipo 3S

Alimentazione ricevitore: 12V oppure lipo 3S

Polarità trasmettitore e ricevitore: Positivo (CENTRALE) – Negativo (ESTERNO)

Per i telecomandi a 2.4Ghz si consiglia l'utilizzo della frequenza da 1.3Ghz e superiore

Installare almeno a 15 cm dalla ricevente radio del modello

Accendere solo con le antenne collegate per evitare la rottura del dispositivo

Se volete alimentare una telecamera CCD con la corrente in uscita dal trasmettitore assicuratevi che anche la telecamera sia 12V

ATTENZIONE

Questo prodotto è destinato per l'uso nelle sole nazioni che consentono l'utilizzo libero della frequenza 1,2/1,3Ghz. In Italia l'uso di tali frequenze non è consentito tranne che per i possessori della patente di radioamatore. In particolare potranno essere usati i soli canali di trasmissione identificati sul nostro trasmettitore come 8 – 9 – H – C. I suddetti canali sono autorizzati alla trasmissione e ricezione ad uso esclusivo dei radioamatori in possesso della patente. Le potenze massime dipendono dalla classe della patente. L'utilizzatore si impegna a trasmettere ciclicamente il suo identificativo durante la trasmissione.

Il trasmettitore viene venduto depotenziato a 10MW per eseguire i relativi test di certificazione CE. Per coloro che vogliono utilizzare la potenza massima indicata nelle specifiche devono annullare il blocco software tenendo premuto il tasto di cambio canale per 5 secondi. In questo modo il trasmettitore utilizzerà la massima potenza dichiarata nelle caratteristiche. L'operazione è irreversibile ed ogni utente la esegue a suo rischio e pericolo consapevole che l'apparecchio perderà tutte le sue certificazioni e la relativa garanzia.

Accettando le condizioni di vendita al momento dell'acquisto di questo prodotto si dichiara di essere in possesso dei requisiti di legge per l'utilizzo dello stesso.

La società Elite Consulting sas con sede legale in Roma declina ogni responsabilità sull'uso illecito di queste apparecchiature.